19-1654; Rev 3; 1/12

MAXIM

Low-Dropout, Low I_Q, 1A Linear Regulator

General Description

The MAX1793 low-dropout linear regulator (LDO) operates from +2.5V to +5.5V and delivers a guaranteed 1A load current with a low 210mV dropout. The high-accuracy (±1%) output voltage is preset at an internally trimmed voltage (see the *Ordering Information*) or can be adjusted from 1.25V to 5.0V with an external resistor-divider.

An internal pMOS pass transistor allows a low 125µA supply current, making the MAX1793 ideal for battery-operated portable equipment. Other features include a built-in reset output, low-power shutdown, and short-circuit and thermal-overload protection. The MAX1793 is available in a 1.5W, 16-pin power TSSOP package, which is 30% smaller than a SOT223 package and only 1.1mm high.

Applications

Notebook Computers

Cordless Telephones

Cellular Phones

Modems

Handheld Instruments

PDAs and Palmtop Computers

Features

- **Guaranteed 1A Output Current**
- **Low 210mV Dropout at 1A**
- **Up to ±1% Output Voltage Accuracy**
  Preset at 1.5V, 1.8V, 2.0V, 2.5V, 3.3V or 5.0V
  Adjustable from 1.25V to 5.0V
- **Reset Output (4ms Delay)**
- **Low 125µA Ground Current**
- **0.1µA Shutdown**
- **Low 115µV_{RMS} Output Noise**
- **Thermal-Overload Protection**
- **Output Current Limit**
- **Tiny TSSOP Power Package (1.5W)**
  30% Smaller than SOT223 (only 1.1mm high)

Ordering Information

PART	TEMP RANGE	PIN-PACKAGE	V_{OUT}† (V)
MAX1793EUE-50	-40°C to +85°C	16 TSSOP-EP*	5.0 or Adj
MAX1793EUE-33	-40°C to +85°C	16 TSSOP-EP*	3.3 or Adj
MAX1793EUE-33/V	-40°C to +85°C	16 TSSOP-EP*	3.3 or Adj

Ordering Information continued at end of data sheet


**EP = Exposed pad.*

†Contact factory for other preset output voltages.


/V Denotes an automotive qualified part.

Note: *Devices are also available in a lead(Pb)-free/RoHS-compliant package. Specify lead-free by adding "+" to the part number when ordering.*

Typical Operating Circuit



Pin Configuration



TSSOP

For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

Low-Dropout, Low IQ, 1A Linear Regulator

ABSOLUTE MAXIMUM RATINGS

IN, $\overline{SHDN}$, $\overline{RST}$ to GND .....-0.3V to +6V
OUT, SET to GND .....-0.3V to (V_{IN} + 0.3V)
Output Short-Circuit Duration .....Infinite
Continuous Power Dissipation (T_A = +70°C)
TSSOP-EP (derate 19mW/°C above +70°C).....1.5W
Operating Temperature Range .....-40°C to +85°C
Junction Temperature.....+150°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering, 10s) .....+300°C
Soldering Temperature (reflow) .....+260°C
Soldering Temperature (reflow)
Lead(Pb)-Free Packages.....+260°C
Packages Containing Lead(Pb).....+240°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{IN} = $V_{OUT(NOM)}$ + 0.5V or V_{IN} = 2.5V (whichever is greater), $\overline{SHDN}$ = IN, **T_A = +0°C to +85°C**, unless otherwise noted. Typical values are at T_A = +25°C.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Voltage	V_{IN}			2.5		5.5	V
Input Undervoltage Lockout	V_{IN}			2.0		2.3	V
Output Voltage Accuracy (Preset Mode, SET = GND)		T_A = +85°C, I_{OUT} = 250mA	Preset $V_{OUT} \geq$ 2.5V	-1		+1	%
			Preset V_{OUT} < 2.5V	-1.5		+1.5	
		T_A = 0°C to +85°C, I_{OUT} = 250mA		-2		+2	
		T_A = 0°C to +85°C, I_{OUT} = 1mA to 1A, $V_{IN} > V_{OUT}$ + 0.5V		-3		+3	
SET Voltage Threshold (For Adjustable Output)		T_A = +85°C, I_{OUT} = 250mA, V_{IN} = 3V		1.229	1.250	1.271	V
		T_A = 0°C to +85°C, I_{OUT} = 250mA, V_{IN} = 3V		1.219		1.281	
		T_A = 0°C to +85°C, I_{OUT} = 1mA to 1A, V_{IN} = 3V		1.212		1.288	
Adjustable Output Voltage Range				1.25		5	V
Maximum Output Current	I_{OUT}	Continuous, $V_{IN} \geq$ 3V		1			A_{RMS}
Short-Circuit Current Limit	I_{LIM}	V_{OUT} = 0V, $V_{IN} \geq$ 3V		1.1	1.8	3.3	A
In-Regulation Current Limit		V_{OUT} within 4% of nominal output voltage, V_{IN} = 5.5V			2.8		A
SET Pin Dual Mode Threshold				50		150	mV
SET Input Bias Current	I_{SET}	V_{SET} = +1.25V				±100	nA
Ground Current	I_{GND}	I_{OUT} = 100µA			125	200	µA
Dropout Voltage (Note 1)	V_{IN} - V_{OUT}	I_{OUT} = 1A, SET = GND	MAX1793-33, -50		210	350	mV
			MAX1793-25		270	450	
Line Regulation	ΔV_{LNR}	V_{IN} from (V_{OUT} + 0.1V) to +5.5V, I_{OUT} = 5mA, SET = GND		-0.15	0	+0.15	%/V
Load Regulation	ΔV_{LDR}	I_{OUT} = 100µA to 1A			0.7		%
Output Voltage Noise		10Hz to 1MHz, C_{OUT} = 6.8µF (ESR < 0.1Ω)			115		μV_{RMS}
Shutdown Supply Current	I_{OFF}	$\overline{SHDN}$ = GND, V_{IN} = +5.5V			0.1	16	µA
Output Pulldown Resistance in Shutdown		$\overline{SHDN}$ = GND			5		kΩ

ELECTRICAL CHARACTERISTICS (continued)

(V_{IN} = $V_{OUT(NOM)}$ + 0.5V or V_{IN} = 2.5V (whichever is greater), $\overline{SHDN}$ = IN, **T_A = +0°C to +85°C**, unless otherwise noted. Typical values are at T_A = +25°C.)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
$\overline{SHDN}$ Input Threshold	V_{IH}	+2.5V < V_{IN} < +5.5V	1.6			V
	V_{IL}				0.6	
$\overline{SHDN}$ Input Bias Current	$I_{\overline{SHDN}}$	$\overline{SHDN}$ = GND or IN		0.01	1	µA
$\overline{RST}$ Output Low Voltage	VOL	I_{SINK} = 1mA			0.1	V
Operating Voltage Range for $\overline{RST}$ Valid		I_{SINK} = 100µA	1.0		5.5	V
$\overline{RST}$ Output High Leakage		$V_{\overline{RST}}$ = +5.5V		0.01	1	µA
$\overline{RST}$ Trip Level Referred to Nominal V_{OUT}		Rising edge	90	94	96	% V_{OUT}
$\overline{RST}$ Release Delay		Rising edge	1.5	4.0	8.0	ms
Thermal Shutdown Temperature	$T_{\overline{SHDN}}$	Typical thermal hysteresis = 20°C		170		°C

ELECTRICAL CHARACTERISTICS

(V_{IN} = $V_{OUT(NOM)}$ + 0.5V or V_{IN} = 2.5V (whichever is greater), $\overline{SHDN}$ = IN, **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Voltage	V_{IN}			2.5		5.5	V
Input Undervoltage Lockout	V_{IN}			2.0		2.3	V
Output Voltage Accuracy (preset mode, SET = GND)		I_{OUT} = 250mA		-2.5		2.5	%
		I_{OUT} = 1mA to 1A, V_{IN} > V_{OUT} + 0.5V		-3.2		3.2	
SET Voltage Threshold (for adjustable output)		I_{OUT} = 250mA, V_{IN} = 3V		1.216		1.284	V
		I_{OUT} = 1mA to 1A, V_{IN} = 3V		1.210		1.290	
Adjustable Output Voltage Range				1.25		5	V
Maximum Output Current	I_{OUT}	Continuous, V_{IN} ≥ 3V		1			A_{RMS}
Short-Circuit Current Limit	I_{LIM}	V_{OUT} = 0V, V_{IN} ≥ 3V		1.1		3.3	A
SET Pin Dual Mode Threshold				50		150	mV
SET Input Bias Current	I_{SET}	V_{SET} = +1.25V				±100	nA
Ground Current	I_{GND}	I_{OUT} = 100µA				200	µA
Dropout Voltage (Note 1)	V_{IN} - V_{OUT}	I_{OUT} = 1A, SET = GND	MAX1793-33, -50			350	mV
			MAX1793-25			450	
Line Regulation	ΔV_{LNR}	V_{IN} from (V_{OUT} + 0.1V) to +5.5V, I_{OUT} = 5mA, SET = GND		-0.15		0.15	%/V
Shutdown Supply Current	I_{OFF}	$\overline{SHDN}$ = GND, V_{IN} = +5.5V				16	µA
$\overline{SHDN}$ Input Threshold	V_{IH}	+2.5V < V_{IN} < +5.5V		1.6			V
	V_{IL}					0.6	
$\overline{SHDN}$ Input Bias Current	$I_{\overline{SHDN}}$	$\overline{SHDN}$ = GND or IN				1	µA
$\overline{RST}$ Output Low Voltage	VOL	I_{SINK} = 1mA				0.1	V

ELECTRICAL CHARACTERISTICS (continued)

(V_{IN} = $V_{OUT(NOM)}$ + 0.5V or V_{IN} = 2.5V (whichever is greater), $\overline{SHDN}$ = IN, **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Operating Voltage Range for $\overline{RST}$ Valid		I_{SINK} = 10µA	1.0		5.5	V
$\overline{RST}$ Output High Leakage		$V_{\overline{RST}}$ = +5.5V			1	µA
$\overline{RST}$ Trip Level Referred to Nominal V_{OUT}		Rising edge	90		96	% V_{OUT}
$\overline{RST}$ Release Delay		Rising edge	1.5		8.0	ms


Note 1: Dropout voltage is defined as V_{IN} - V_{OUT}, when V_{OUT} is 100mV below the value of V_{OUT} measured when V_{IN} = $V_{OUT(NOM)}$ + 0.5V. Since the minimum input voltage is 2.5V, this specification in only meaningful when $V_{OUT(NOM)}$ ≥2.5V. For $V_{OUT(NOM)}$ between 2.5V and 3.3V, use the following equations: Typical Dropout = 210mV + (3.3V - $V_{OUT(NOM)}$ x 75mV/V; Guaranteed Maximum Dropout = 350mV + (3.3V - $V_{OUT(NOM)}$ x 125mV/V. For $V_{OUT(NOM)}$ > 3.3V: Typical Dropout = 210mV; Guaranteed Maximum Dropout = 350mV.

Note 2: Specifications to T_A = -40°C are guaranteed by design and not production tested.


Typical Operating Characteristics

(Circuit of Figure 2, V_{IN} = +5V, $V_{\overline{SHDN}}$ = V_{IN}, V_{OUT} = +3.3V, T_A = +25°C, unless otherwise noted.)


OUTPUT VOLTAGE vs. LOAD CURRENT




OUTPUT VOLTAGE vs. INPUT VOLTAGE




OUTPUT VOLTAGE vs. TEMPERATURE




GROUND CURRENT vs. INPUT VOLTAGE



GROUND CURRENT vs. LOAD CURRENT




GROUND CURRENT vs. TEMPERATURE




Typical Operating Characteristics (continued)

(Circuit of Figure 2, V_{IN} = +5V, $V_{\overline{SHDN}} = V_{IN}$, V_{OUT} = +3.3V, T_A = +25°C, unless otherwise noted.)


DROPOUT VOLTAGE vs. LOAD CURRENT




POWER-SUPPLY REJECTION RATIO vs. FREQUENCY




OUTPUT NOISE SPECTRAL DENSITY vs. FREQUENCY




OUTPUT NOISE vs. LOAD CURRENT




LINE-TRANSIENT RESPONSE



LOAD-TRANSIENT RESPONSE




OUTPUT NOISE




Low-Dropout, Low IQ, 1A Linear Regulator

Typical Operating Characteristics (continued)

(Circuit of Figure 2, V_{IN} = +5V, $V_{\overline{SHDN}} = V_{IN}$, V_{OUT} = +3.3V, T_A = +25°C, unless otherwise noted.)





Pin Description

PIN	NAME	FUNCTION
1, 8, 9, 16	N.C.	No Connection. Not internally connected.
2–5	IN	Regulator Input. Supply voltage ranges from +2.5V to +5.5V. Bypass with a 4.7µF capacitor to GND (see the *Capacitor Selection and Regulator Stability*). These inputs are internally connected, but they also must be externally connected for proper operation.
6	$\overline{RST}$	Reset Output. Open-drain output is low when V_{OUT} is 6% below its nominal value. $\overline{RST}$ remains low while the output voltage (V_{OUT}) is below the reset threshold and for at least 4ms after V_{OUT} rises above the reset threshold. Connect a 100kΩ pullup resister to OUT to obtain an output voltage.
7	$\overline{SHDN}$	Active-Low Shutdown Input. A logic-low disables the output and reduces the supply current to 0.1µA. In shutdown, the $\overline{RST}$ output is low and OUT is pulled low through an internal 5kΩ resistance. Connect $\overline{SHDN}$ to IN for normal operation.
10	GND	Ground. This pin and the exposed pad also function as a heatsink. Solder both to a large pad or to the circuit-board ground plane to maximize power dissipation.
11	SET	Voltage-Setting Input. Connect to GND to select the factory-present output voltage. Connect SET to an external resistor-divider for adjustable-output operation.
12–15	OUT	Regulator Output. Bypass with a 6.8µF, low-ESR capacitor to GND. Connect all OUT pins together at the IC.
—	EP	Exposed Pad. Connect to the ground plane. EP also functions as a heatsink. Solder to the circuit-board ground plane to maximize thermal dissipation.

Detailed Description

The MAX1793 features Dual Mode™ operation, allowing a fixed output or an adjustable output from +1.25V to +5V. The regulators are guaranteed to supply 1A of output current.

As Figure 1 shows, the device consists of a +1.25V reference, error amplifier, MOSFET driver, p-channel pass transistor, internal feedback voltage-divider, Dual Mode comparator, and 4ms reset output.

The +1.25V reference is connected to the inverting input of the error amplifier. The error amplifier compares this reference with the selected feedback voltage and amplifies the difference. The MOSFET driver reads the error signal and applies the appropriate drive to the p-channel transistor. If the feedback voltage is lower than the reference, the pass transistor's gate is pulled lower, allowing more current to pass and increase the output voltage. If the feedback voltage is high, the pass transistor's gate is pulled up, allowing less current to pass to the output. The low V_{OUT} comparator senses when the feedback voltage has dropped 6% below its expected level, causing $\overline{RST}$ to go low.

The output voltage is fed back through either an internal resistor-divider connected to OUT or an external resistor network connected to SET. The Dual Mode comparator examines V_{SET} and selects the feedback path. If V_{SET} is below 50mV, the internal feedback path is used and the output is regulated to the factory-preset voltage.

Dual Mode is a trademark of Maxim Integrated Products, Inc.




Figure 1. Functional Diagram

Low-Dropout, Low I_Q, 1A Linear Regulator

Internal p-Channel Pass Transistor

The MAX1793 features a 1A p-channel MOSFET pass transistor. Unlike similar designs using pnp pass transistors, p-channel MOSFETs require no base drive, which reduces quiescent current. pnp-based regulators also waste considerable current in dropout when the pass transistor saturates and use high base-drive currents under large loads. The MAX1793 does not suffer from these problems and consumes only 225µA of quiescent current under heavy loads, as well as in dropout.

Output Voltage Selection

The MAX1793 features Dual Mode operation. In preset voltage mode, the output of the MAX1793 is set to an internally trimmed voltage (see the *Ordering Information*). Select this mode by connecting SET to GND (Figure 2).

In adjustable mode, an output is selected between +1.25V and +5V using two external resistors connected as a voltage-divider to SET (Figure 3). The output voltage is determined by the following equation:

$$V_{OUT} = V_{SET} [1 + (R1/R2)]$$

where V_{SET} = +1.25V. To simplify resistor selection:

$$R1 = R2 [(V_{OUT}/V_{SET}) - 1]$$

Since the input bias current at SET is less than 100nA, large resistance values can be used for R1 and R2 to minimize power consumption without losing efficiency. Up to 125kΩ is acceptable for R2.

In preset voltage mode, the impedance from SET to GND should be less than 10kΩ. Otherwise, spurious conditions could cause the voltage at SET to exceed the 50mV dual-mode threshold.

Shutdown

A logic-low on $\overline{SHDN}$ disables the MAX1793. In shutdown, the pass transistor, control circuitry, reference, and all internal circuits are turned off, reducing supply current to typically 0.1µA. Connect $\overline{SHDN}$ to IN for normal operation. In shutdown, $\overline{RST}$ goes low and OUT is discharged to GND with a 5kΩ internal resistance.

$\overline{RST}$ Comparator

The MAX1793 features a low V_{OUT} indicator that asserts when the output voltage falls out of regulation. The open-drain $\overline{RST}$ output goes low when OUT falls 6% below its nominal output voltage. $\overline{RST}$ remains low for 4ms after OUT has returned to its nominal value. A 100kΩ pullup resistor from $\overline{RST}$ to a suitable logic supply voltage (typically OUT) provides a logic control signal. $\overline{RST}$ can be used as a power-on-reset (POR) signal to a microcontroller or can drive an external LED to indicate power failure. $\overline{RST}$ is low during shutdown.

Current Limiting

The MAX1793 features a current limit that monitors the pass transistor, typically limiting short-circuit output current to 1.8A. The current limit is increased to approximately 2.8A when the output voltage is in regulation, improving performance with large transient loads. The output can be shorted to ground for an indefinite period of time without damaging the device.

Thermal-Overload Protection

Thermal-overload protection limits total power dissipation in the MAX1793. When the junction temperature exceeds T_J = +170°C, a thermal sensor turns off the pass transistor, allowing the IC to cool. The thermal sensor turns the pass transistor on once the IC's junction temperature drops approximately 20°C. Continuous short-circuit conditions will result in a pulsed output.




Figure 2. Typical Operating Circuit with Preset Output Voltage




Figure 3. Typical Operating Circuit with Adjustable Output Voltage

Thermal-overload protection is designed to safeguard the MAX1793 in the event of fault conditions. For continuous operation, do not exceed the absolute maximum junction-temperature rating of T_J = +150°C.

Operating Region and Power Dissipation

Maximum power dissipation of the MAX1793 depends on the thermal resistance of the case and circuit board, the temperature difference between the die junction and ambient air, and the rate of air flow. The power dissipated by the device is: $P = I_{OUT} (V_{IN} - V_{OUT})$. The resulting maximum power dissipation is:

$$P_{MAX} = [(T_{J(MAX)} - T_A)/(\theta_{JC} + \theta_{CA})]$$

where $(T_{J(MAX)} - T_A)$ is the temperature difference between the maximum allowed die junction (+150°C) and the surrounding air, θ_{JC} (junction-to-case) is the thermal resistance of the package chosen, and θ_{CA} is the thermal resistance from the case through the PCB, copper traces, and other materials to the surrounding air. Figure 4 shows allowable power dissipation for typical PCBs at +25°C, +50°C, and +70°C ambient temperatures.

The MAX1793 TSSOP-EP package features an exposed thermal pad on its underside. This pad lowers the thermal resistance of the package by providing a direct heat conduction path from the die to the PCB. Additionally, the ground pin (GND) also channels heat. Connect the exposed thermal pad and GND to circuit ground by using a large pad (minimum 1in^2 recommended), or multiple vias to the ground plane.

Applications Information

Capacitor Selection and Regulator Stability

Capacitors are required at the input and output of the MAX1793. Connect a 4.7µF capacitor between IN and ground (C_{IN}) and a 6.8µF capacitor between OUT and ground (C_{OUT}). C_{IN} serves only to lower the source impedance of the input supply and may be smaller than 4.7µF when the MAX1793 is powered from regulated power supplies or low-impedance batteries.

The output capacitor's equivalent series resistance (ESR) affects stability and output noise. C_{OUT} ESR should be 0.5Ω or less to ensure stability and optimum transient response. Surface-mount ceramic capacitors have very low ESR and are commonly available in values up to 10µF. Other low-ESR (< 0.5Ω) capacitors, such as surface-mount tantalum or OS-CON, may also be used. Connect C_{IN} and C_{OUT} as close to the IC as possible to minimize the impact of PCB trace inductance.




Figure 4. Power Operating Region: Maximum Output Current vs. Input-Output Differential Voltage

Noise, PSRR, and Transient Response

The MAX1793 output noise is typically 115µV_{RMS} during normal operation. This is suitably low for most applications. See the output noise plot in the *Typical Operating Characteristics*.

The MAX1793 is designed to achieve low dropout voltage and low quiescent current in battery-powered systems while still maintaining good noise, transient response, and AC rejection. See the *Typical Operating Characteristics* for a plot of Power-Supply Rejection Ratio (PSRR) vs. Frequency. When operating from very noisy sources, supply noise rejection and transient response can be improved by increasing the values of the input and output capacitors and employing passive postfiltering.

Input-Output (Dropout) Voltage

A regulator's minimum input-to-output voltage differential (dropout voltage) determines the lowest usable supply voltage. In battery-powered systems, this determines the useful end-of-life battery voltage. Since a p-channel MOSFET is used as the pass device, dropout voltage is the product of $R_{DS(ON)}$ and load current (see the *Electrical Characteristics* and Dropout Voltage vs. Load Current in the *Typical Operating Characteristics*). The MAX1793 operating current typically remains below 225µA in dropout.

Low-Dropout, Low IQ, 1A Linear Regulator

Ordering Information (continued)

PART	TEMP RANGE	PIN-PACKAGE	VOUT† (V)
MAX1793EUE-25	-40°C to +85°C	16 TSSOP-EP*	2.5 or Adj
MAX1793EUE-20	-40°C to +85°C	16 TSSOP-EP*	2.0 or Adj
MAX1793EUE-18	-40°C to +85°C	16 TSSOP-EP*	1.8 or Adj
MAX1793EUE-15	-40°C to +85°C	16 TSSOP-EP*	1.5 or Adj

*EP = Exposed pad.

†Contact factory for other preset output voltages.

/V Denotes an automotive qualified part.

Note: *Devices are also available in a lead(Pb)-free/RoHS-compliant package. Specify lead-free by adding "+" to the part number when ordering.*

Package Information

For the latest package outline information and land patterns (footprints), go to **www.maxim-ic.com/packages**. Note that a "+", "#", or "-" in the package code indicates RoHS status only. Package drawings may show a different suffix character, but the drawing pertains to the package regardless of RoHS status.

PACKAGE TYPE	PACKAGE CODE	OUTLINE NO.	LAND PATTERN NO.
16 TSSOP-EP	U16E-3	**21-0108**	**90-0120**

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	8/00	Initial release	—
1	11/00	Added output voltages and updated *Electrical Characteristics*.	1–4, 7–9
2	9/09	Added the automotive version of the MAX1793.	1
3	1/12	Added lead-free options and updated soldering temperature and *Pin Description*	1, 2, 6, 10

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time. The parametric values (min and max limits) shown in the Electrical Characteristics table are guaranteed. Other parametric values quoted in this data sheet are provided for guidance.

© 2012 Maxim Integrated Products Maxim is a registered trademark of Maxim Integrated Products, Inc.