We are still shipping! When you place an order, we will ship as quickly as possible. We are actively monitoring the COVID-19 situation; please see all updates here. Thank you for your continued support.







images are CC BY 2.0

SHARE

9.0" Display Module w/ Resistive Touch for Arduino

LCD-15982 ROHS

DESCRIPTION | INCLUDES | FEATURES | DOCUMENTS

- Powerful 9.0” Intelligent LCD-TFT display module powered by DIABLO16.
- 800 x 480 Resolution, RGB 65K true to life colours, TFT Screen with integrated 4-wire Resistive Touch Panel (DT).
- 6 banks of 32750 bytes of Flash memory for User Application Code and Data.
- 32Kb of SRAM purely for the User.
- 16 General Purpose I/O pins for user interfacing, which include 4 configurable Analog Inputs.
- The GPIO is variously configurable for alternative functions such as:
  - 3x I2C channels available.
  - 1x SPI dedicated for SD Card and 3x configurable SPI channels available.
  - 1x dedicated and 3x configurable TTL Serial comm ports available.
  - Up to 6 GPIO can be used as Pin Counters.
  - Up to 6 GPIO for PWM (simple and Servo).
  - Up to 10 GPIO for Pulse Output.
  - Up to 14 GPIO can be configured for Quadrature Encoder Inputs (2 channels).
- 30pin FPC connection, for all signals, power, communications, GPIO and programming.
- On-board latch type micro-SD memory card connector for multimedia storage and data logging purposes.
- DOS compatible file access (FAT16 format) as well as low level access to card memory.
- Dedicated PWM Audio pin driven by WAV files from micro-SD card, and for sound generation, for an external amplifier.
- Display full colour images, animations, icons and video clips.
- Supports all available Windows fonts.
- 4.0V to 5.5V range operation (single supply).
- Module dimensions: 230.7 x 126.4 x 7.9mm (Thickness is 4.9mm LCD + 3.0mm PCB).
- 4x metal mounting tabs with 4.2mm holes for mechanical mounting using M4 screws.

Tags

4D SYSTEMS | LCD

COMMENTS 0 | REVIEWS 0

Comments

Looking for answers to technical questions?

We welcome your comments and suggestions below. However, if you are looking for solutions to technical questions please see our Technical Assistance page.

Log in or register to post comments.



STAY IN TOUCH WITH US

Email address SUBMIT

Weekly product releases, special offers, and more.








ABOUT SPARKFUN

- Read Our Story
- Press & Media
- SparkFun Education
- Job Openings

PARTNER WITH US

- See Our Partners
- Become a Distributor/Reseller
- Receive Volume Discounts
- Build a Custom Kit
- Apply for a Hardware Donation

SUPPORT

- Customer Support
- Purchase Orders & Payment
- Terms
- Technical Assistance
- FAQs
- Contact Us

SITE INFORMATION

- Terms of Service
- Privacy Policy
- Compliance
- Site Map

SparkFun Electronics ® / **6333 Dry Creek Parkway, Niwot, Colorado 80503**

Questions? Feedback? powered by Olark live chat software