300W PowerVerter Ultra-Compact Inverter - Portable Power for All Applications

MODEL NUMBER: **PV300**

Description

Harness your vehicle's battery to efficiently power office equipment on the road. Continuously supplies up to 300 watts of 120V AC power to 2 AC outlets from any 12V battery or automotive DC source. Convenient cigarette lighter DC input jack with 3-ft. cable provides one-step installation. Super-compact, lightweight metal case design is among the smallest, most rugged inverters available.

Features

- Allows users to run AC appliances from any 12V cigarette lighter socket
- Converts 12V DC battery power to 120V AC power
- 300 watts continuous output power; 500 watts peak output power
- 2 outlet
- 3-ft. cord with cigarette-lighter plug
- Ultra compact, lightweight design with all-metal housing
- Low battery alarm with auto-shutoff prevents deep battery discharge
- 30-amp fuse protects inverter from overload
- Lighted power switch

Highlights

- 12V DC input; 120V AC output; 2 outlets
- 300 watts continuous output
- Convenient cigarette lighter plug

Package Includes

- PV300 Inverter
- Warranty information
- Instruction manual

Specifications

OVERVIEW	
UPC Code	037332050281
INPUT	
Voltage Compatibility (VDC)	12
OUTPUT	
Pure Sine Wave Output	No
Nominal Output Voltage(s) Supported	120V
Output Receptacles	(2) 5-15R
Continuous Output Capacity (Watts)	300
PHYSICAL	
Shipping Dimensions (hwd / in.)	8.12 x 1.50 x 11.50
Shipping Dimensions (hwd / cm)	20.64 x 3.81 x 29.21
Shipping Weight (lbs.)	2.00
Shipping Weight (kg)	0.91

1000 Eaton Boulevard
Cleveland, OH 44122
United States
https://tripplite.eaton.com

© 2025 Eaton. All Rights Reserved.
Eaton is a registered trademark. All other trademarks
are the property of their respective owners.